



ADL-HAZ - Advantage Downlight

ADL-HAZ PERFORMANCE TABLE

| <u>Catalog Number</u> | <u>Delivered Lumens</u> | <u>Watts</u> | <u>Efficiency</u> |
|---------------------------|-------------------------|--------------|-------------------|
| ADL-FS1-0750lm-4R-HAZ-30 | 797 | 9 | 89 |
| ADL-FS1-0750lm-4R-HAZ-35 | 900 | 9 | 100 |
| ADL-FS1-0750lm-4R-HAZ-40 | 866 | 9 | 96 |
| ADL-FS1-0750lm-4S-HAZ-30 | 756 | 9 | 84 |
| ADL-FS1-0750lm-4S-HAZ-35 | 854 | 9 | 95 |
| ADL-FS1-0750lm-4S-HAZ-40 | 821 | 9 | 91 |
| ADL-FS1-0750lm-4W-HAZ-30 | 794 | 9 | 88 |
| ADL-FS1-0750lm-4W-HAZ-35 | 897 | 9 | 100 |
| ADL-FS1-0750lm-4W-HAZ-40 | 863 | 9 | 96 |
| ADL-FS1-0750lm-4WS-HAZ-30 | 751 | 9 | 83 |
| ADL-FS1-0750lm-4WS-HAZ-35 | 849 | 9 | 94 |
| ADL-FS1-0750lm-4WS-HAZ-40 | 817 | 9 | 91 |
| ADL-FS1-0750lm-6R-HAZ-30 | 855 | 9 | 95 |
| ADL-FS1-0750lm-6R-HAZ-35 | 967 | 9 | 107 |
| ADL-FS1-0750lm-6R-HAZ-40 | 930 | 9 | 103 |
| ADL-FS1-0750lm-6S-HAZ-30 | 805 | 9 | 89 |
| ADL-FS1-0750lm-6S-HAZ-35 | 909 | 9 | 101 |
| ADL-FS1-0750lm-6S-HAZ-40 | 875 | 9 | 97 |
| ADL-FS1-0750lm-8R-HAZ-30 | 858 | 9 | 95 |
| ADL-FS1-0750lm-8R-HAZ-35 | 970 | 9 | 108 |
| ADL-FS1-0750lm-8R-HAZ-40 | 933 | 9 | 104 |
| | | | |
| ADL-FS1-1200lm-4R-HAZ-30 | 1,102 | 13 | 85 |
| ADL-FS1-1200lm-4R-HAZ-35 | 1,245 | 13 | 96 |
| ADL-FS1-1200lm-4R-HAZ-40 | 1,198 | 13 | 92 |
| ADL-FS1-1200lm-4S-HAZ-30 | 1,046 | 13 | 80 |
| ADL-FS1-1200lm-4S-HAZ-35 | 1,182 | 13 | 91 |
| ADL-FS1-1200lm-4S-HAZ-40 | 1,138 | 13 | 88 |
| ADL-FS1-1200lm-4W-HAZ-30 | 1,100 | 13 | 85 |
| ADL-FS1-1200lm-4W-HAZ-35 | 1,243 | 13 | 96 |
| ADL-FS1-1200lm-4W-HAZ-40 | 1,196 | 13 | 92 |
| ADL-FS1-1200lm-4WS-HAZ-30 | 1,040 | 13 | 80 |
| ADL-FS1-1200lm-4WS-HAZ-35 | 1,175 | 13 | 90 |
| ADL-FS1-1200lm-4WS-HAZ-40 | 1,131 | 13 | 87 |
| ADL-FS1-1200lm-6R-HAZ-30 | 1,184 | 13 | 91 |
| ADL-FS1-1200lm-6R-HAZ-35 | 1,338 | 13 | 103 |
| ADL-FS1-1200lm-6R-HAZ-40 | 1,287 | 13 | 99 |
| ADL-FS1-1200lm-6S-HAZ-30 | 1,115 | 13 | 86 |
| ADL-FS1-1200lm-6S-HAZ-35 | 1,259 | 13 | 97 |
| ADL-FS1-1200lm-6S-HAZ-40 | 1,211 | 13 | 93 |
| ADL-FS1-1200lm-8R-HAZ-30 | 1,188 | 13 | 91 |
| ADL-FS1-1200lm-8R-HAZ-35 | 1,342 | 13 | 103 |
| ADL-FS1-1200lm-8R-HAZ-40 | 1,291 | 13 | 99 |
| | | | |
| ADL-FS1-1800lm-4R-HAZ-30 | 1,439 | 19 | 76 |
| ADL-FS1-1800lm-4R-HAZ-35 | 1,626 | 19 | 86 |
| ADL-FS1-1800lm-4R-HAZ-40 | 1,564 | 19 | 82 |
| ADL-FS1-1800lm-4S-HAZ-30 | 1,366 | 19 | 72 |
| ADL-FS1-1800lm-4S-HAZ-35 | 1,543 | 19 | 81 |
| ADL-FS1-1800lm-4S-HAZ-40 | 1,485 | 19 | 78 |



ADL-HAZ - Advantage Downlight

ADL-HAZ PERFORMANCE TABLE

| <u>Catalog Number</u> | <u>Delivered Lumens</u> | <u>Watts</u> | <u>Efficiency</u> |
|---------------------------|-------------------------|--------------|-------------------|
| ADL-FS1-1800lm-4W-HAZ-30 | 1,436 | 19 | 76 |
| ADL-FS1-1800lm-4W-HAZ-35 | 1,622 | 19 | 85 |
| ADL-FS1-1800lm-4W-HAZ-40 | 1,561 | 19 | 82 |
| ADL-FS1-1800lm-4WS-HAZ-30 | 1,359 | 19 | 72 |
| ADL-FS1-1800lm-4WS-HAZ-35 | 1,535 | 19 | 81 |
| ADL-FS1-1800lm-4WS-HAZ-40 | 1,477 | 19 | 78 |
| ADL-FS1-1800lm-6R-HAZ-30 | 1,548 | 19 | 81 |
| ADL-FS1-1800lm-6R-HAZ-35 | 1,749 | 19 | 92 |
| ADL-FS1-1800lm-6R-HAZ-40 | 1,682 | 19 | 89 |
| ADL-FS1-1800lm-6S-HAZ-30 | 1,455 | 19 | 77 |
| ADL-FS1-1800lm-6S-HAZ-35 | 1,644 | 19 | 87 |
| ADL-FS1-1800lm-6S-HAZ-40 | 1,581 | 19 | 83 |
| ADL-FS1-1800lm-8R-HAZ-30 | 1,552 | 19 | 82 |
| ADL-FS1-1800lm-8R-HAZ-35 | 1,753 | 19 | 92 |
| ADL-FS1-1800lm-8R-HAZ-40 | 1,686 | 19 | 89 |
| | | | |
| ADL-FS2-2200lm-4R-HAZ-30 | 2,362 | 26 | 91 |
| ADL-FS2-2200lm-4R-HAZ-35 | 2,659 | 26 | 102 |
| ADL-FS2-2200lm-4R-HAZ-40 | 2,508 | 26 | 96 |
| ADL-FS2-2200lm-4S-HAZ-30 | 2,244 | 26 | 86 |
| ADL-FS2-2200lm-4S-HAZ-35 | 2,526 | 26 | 97 |
| ADL-FS2-2200lm-4S-HAZ-40 | 2,383 | 26 | 92 |
| ADL-FS2-2200lm-4W-HAZ-30 | 2,358 | 26 | 91 |
| ADL-FS2-2200lm-4W-HAZ-35 | 2,654 | 26 | 102 |
| ADL-FS2-2200lm-4W-HAZ-40 | 2,503 | 26 | 96 |
| ADL-FS2-2200lm-4WS-HAZ-30 | 2,228 | 26 | 86 |
| ADL-FS2-2200lm-4WS-HAZ-35 | 2,510 | 26 | 97 |
| ADL-FS2-2200lm-4WS-HAZ-40 | 2,368 | 26 | 91 |
| ADL-FS2-2200lm-6R-HAZ-30 | 2,540 | 26 | 98 |
| ADL-FS2-2200lm-6R-HAZ-35 | 2,859 | 26 | 110 |
| ADL-FS2-2200lm-6R-HAZ-40 | 2,697 | 26 | 104 |
| ADL-FS2-2200lm-6S-HAZ-30 | 2,389 | 26 | 92 |
| ADL-FS2-2200lm-6S-HAZ-35 | 2,689 | 26 | 103 |
| ADL-FS2-2200lm-6S-HAZ-40 | 2,536 | 26 | 98 |
| ADL-FS2-2200lm-8R-HAZ-30 | 2,547 | 26 | 98 |
| ADL-FS2-2200lm-8R-HAZ-35 | 2,867 | 26 | 110 |
| ADL-FS2-2200lm-8R-HAZ-40 | 2,705 | 26 | 104 |
| | | | |
| ADL-FS2-2800lm-4R-HAZ-30 | 2,806 | 31 | 91 |
| ADL-FS2-2800lm-4R-HAZ-35 | 3,158 | 31 | 102 |
| ADL-FS2-2800lm-4R-HAZ-40 | 2,974 | 31 | 96 |
| ADL-FS2-2800lm-4S-HAZ-30 | 2,666 | 31 | 86 |
| ADL-FS2-2800lm-4S-HAZ-35 | 3,001 | 31 | 97 |
| ADL-FS2-2800lm-4S-HAZ-40 | 2,831 | 31 | 91 |
| ADL-FS2-2800lm-4W-HAZ-30 | 2,801 | 31 | 90 |
| ADL-FS2-2800lm-4W-HAZ-35 | 3,153 | 31 | 102 |
| ADL-FS2-2800lm-4W-HAZ-40 | 2,974 | 31 | 96 |
| ADL-FS2-2800lm-4WS-HAZ-30 | 2,648 | 31 | 85 |
| ADL-FS2-2800lm-4WS-HAZ-35 | 2,982 | 31 | 96 |
| ADL-FS2-2800lm-4WS-HAZ-40 | 2,813 | 31 | 91 |



ADL-HAZ - Advantage Downlight

ADL-HAZ PERFORMANCE TABLE

| <u>Catalog Number</u> | <u>Delivered Lumens</u> | <u>Watts</u> | <u>Efficiency</u> |
|---------------------------|-------------------------|--------------|-------------------|
| ADL-FS2-2800lm-6R-HAZ-30 | 3,017 | 31 | 97 |
| ADL-FS2-2800lm-6R-HAZ-35 | 3,406 | 31 | 110 |
| ADL-FS2-2800lm-6R-HAZ-40 | 3,398 | 31 | 110 |
| ADL-FS2-2800lm-6S-HAZ-30 | 2,838 | 31 | 92 |
| ADL-FS2-2800lm-6S-HAZ-35 | 3,194 | 31 | 103 |
| ADL-FS2-2800lm-6S-HAZ-40 | 3,013 | 31 | 97 |
| ADL-FS2-2800lm-8R-HAZ-30 | 3,026 | 31 | 98 |
| ADL-FS2-2800lm-8R-HAZ-35 | 3,407 | 31 | 110 |
| ADL-FS2-2800lm-8R-HAZ-40 | 3,214 | 31 | 104 |
| ADL-FS2-3900lm-4R-HAZ-30 | 3,231 | 38 | 85 |
| ADL-FS2-3900lm-4R-HAZ-35 | 3,638 | 38 | 96 |
| ADL-FS2-3900lm-4R-HAZ-40 | 3,432 | 38 | 90 |
| ADL-FS2-3900lm-4S-HAZ-30 | 3,071 | 38 | 81 |
| ADL-FS2-3900lm-4S-HAZ-35 | 3,457 | 38 | 91 |
| ADL-FS2-3900lm-4S-HAZ-40 | 3,260 | 38 | 86 |
| ADL-FS2-3900lm-4W-HAZ-30 | 3,226 | 38 | 85 |
| ADL-FS2-3900lm-4W-HAZ-35 | 3,632 | 38 | 96 |
| ADL-FS2-3900lm-4W-HAZ-40 | 3,426 | 38 | 90 |
| ADL-FS2-3900lm-4WS-HAZ-30 | 3,071 | 38 | 81 |
| ADL-FS2-3900lm-4WS-HAZ-35 | 3,434 | 38 | 90 |
| ADL-FS2-3900lm-4WS-HAZ-40 | 3,240 | 38 | 85 |
| ADL-FS2-3900lm-6R-HAZ-30 | 3,475 | 38 | 91 |
| ADL-FS2-3900lm-6R-HAZ-35 | 3,914 | 38 | 103 |
| ADL-FS2-3900lm-6R-HAZ-40 | 3,690 | 38 | 97 |
| ADL-FS2-3900lm-6S-HAZ-30 | 3,269 | 38 | 86 |
| ADL-FS2-3900lm-6S-HAZ-35 | 3,680 | 38 | 97 |
| ADL-FS2-3900lm-6S-HAZ-40 | 3,471 | 38 | 91 |
| ADL-FS2-3900lm-8R-HAZ-30 | 3,485 | 38 | 92 |
| ADL-FS2-3900lm-8R-HAZ-35 | 3,924 | 38 | 103 |
| ADL-FS2-3900lm-8R-HAZ-40 | 3,700 | 38 | 97 |